

Resistori

RESISTORI FUSIBILI 1W $\pm 5\%$ 6.8K Ω

RESISTENZE FUS 1W J N 6K8

Codice Adimpex: **AOF20268-R**

P/N: **FRN01WJ010JA10**



Outline & Dimension



Type	Dimension(mm)				Pitch	Maximum Withstanding Voltage	Tolerance	Resistance Range
	D	L	d ± 0.05	B ± 3				
FRN 1/4W	2.5 ± 0.5	6.5 ± 1.0	0.60	28	S2	300V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 1/2W	2.5 ± 0.5	6.5 ± 1.0	0.60	28	S2	300V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 3/4W	2.5 ± 0.5	6.5 ± 1.0	0.60	28	S2	300V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 1W	3.0 ± 0.5	9.0 ± 1.0	0.60	28	S2	350V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 1/4W	3.5 ± 0.6	9.5 ± 1.0	0.54	28	S2	350V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 1/2W	3.5 ± 0.6	9.5 ± 1.0	0.54	28	S2	350V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 3/4W	4.0 ± 0.6	11.5 ± 1.0	0.70	25	S2	400V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 1W	4.0 ± 0.6	11.5 ± 1.0	0.70	25	S2	400V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 1W	5.0 ± 0.6	15.5 ± 1.0	0.80	28	44	400V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω

Caratteristiche Tecniche:

Tolleranza:	$\pm 5\%$
Potenza (W):	1 W
Dimensione (mm):	3.5x9.5
Resistenza (Ohm):	6.8K
Tipologia:	Fusibili (FRN)
Gamma:	Resistori tradizionali