

Resistori

RESISTORI FUSIBILI 3W $\pm 5\%$ 5.6 Ω

RESISTENZE FUS 3W J N 5R6

Codice Adimpex: **AOF30.56-R**

P/N: **FRN03WJ056JA19**



Outline & Dimension



Type	Dimension(mm)				Pitch	Dissipative Wattage	Tolerance	Resistance Range
	D	L	d ± 0.05	Pin3				
FRN 1/4W	2.5 ± 0.5	6.5 ± 1.0	0.60	28	52	300W	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 1/8W	2.5 ± 0.5	6.5 ± 1.0	0.60	28	52	300W	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 1/10W	2.5 ± 0.5	6.5 ± 1.0	0.60	28	52	300W	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 1/2W	3.0 ± 0.5	9.0 ± 1.0	0.60	28	52	350W	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 3/4W	3.5 ± 0.6	9.5 ± 1.0	0.54	28	52	350W	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 1W	3.5 ± 0.6	9.5 ± 1.0	0.54	28	52	350W	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 1.5W	4.5 ± 0.6	11.5 ± 1.0	0.70	25	52	400W	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 2W	4.5 ± 0.6	11.5 ± 1.0	0.70	25	52	400W	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω
FRN 3W	5.0 ± 0.6	12.5 ± 1.0	0.80	28	64	400W	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10K Ω

Caratteristiche Tecniche:

Tolleranza:	$\pm 5\%$
Potenza (W):	3 W
Resistenza (Ohm):	5.6
Dimensione (mm):	5x15.5
Tipologia:	Fusibili (FRN)
Gamma:	Resistori tradizionali