

Resistori

RESISTORI FUSIBILI 3W $\pm 5\%$ 6.8 Ω

RESISTENZE FUS 3W J N 6R8

Codice Adimpex: **AOF30.68-R**

P/N: **FRN03WJ068JA19**



Outline & Dimension



Type	Dimension(mm)				Pitch	Insulation Withstanding Voltage	Tolerance	Resistance Range
	D	L	d ± 0.05	B ± 3				
FRN 1/4W	2.5 ± 0.5	6.5 ± 1.0	0.60	28	52	300V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10k Ω
FRN 1/2W	2.5 ± 0.5	6.5 ± 1.0	0.60	28	52	300V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10k Ω
FRN 3/4W	2.5 ± 0.5	6.5 ± 1.0	0.60	28	52	300V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10k Ω
FRN 1W	3.0 ± 0.5	9.0 ± 1.0	0.60	28	52	350V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10k Ω
FRN 3/4W	3.5 ± 0.6	9.5 ± 1.0	0.54	28	52	350V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10k Ω
FRN 1W	3.5 ± 0.6	9.5 ± 1.0	0.54	28	52	350V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10k Ω
FRN 1.5W	4.5 ± 0.6	11.5 ± 1.0	0.70	25	52	400V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10k Ω
FRN 2W	4.5 ± 0.6	11.5 ± 1.0	0.70	25	52	400V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10k Ω
FRN 3W	5.0 ± 0.6	12.5 ± 1.0	0.80	28	64	400V	$\pm 2\%$, $\pm 5\%$, $\pm 10\%$	0.22 Ω -10k Ω

Caratteristiche Tecniche:

Tolleranza:	$\pm 5\%$
Potenza (W):	3 W
Dimensione (mm):	5x15.5
Resistenza (Ohm):	6.8
Tipologia:	Fusibili (FRN)
Gamma:	Resistori tradizionali